



BEARING PART NUMBER	B	C	D	E	F	HOUSING BORE FITS +.0000 -.0005	ULTIMATE STATIC RADIAL LOAD IN LBS.	BALL DIA. (REF.)
	BORE +.0000 -.0005	OUTSIDE DIAMETER +.0000 -.0005	BALL WIDTH +.000 -.005	RACE WIDTH +.010 -.000	CHAMF. MIN.			
BLR-3000	.1900	.6250	.437	.322	.020	.6250	3,200	.531
BLR-3015	.1900	.5000	.359	.281	.020	.5000	3,000	.437
BLR-4000	.2500	.6250	.437	.322	.020	.6250	5,500	.531
BLR-5000	.3125	.6875	.437	.312	.020	.6875	8,600	.593
BLR-6000A	.3750	.8125	.500	.401	.020	.8125	13,200	.687
BLR-7000	.4375	.9375	.562	.437	.020	.9375	16,900	.781
BLR-8000	.5000	1.0000	.625	.500	.020	1.0000	22,000	.875
BLR-9000	.5625	1.1250	.687	.531	.020	1.1250	29,100	1.000
BLR-10000	.6250	1.1875	.750	.562	.020	1.1875	34,500	1.062
BLR-12000	.7500	1.3750	.875	.625	.020	1.3750	49,500	1.250
BLR-14000	.8750	1.6250	.875	.750	.020	1.6250	67,600	1.375
BLR-16000	1.0000	2.1250	1.375	1.000	.020	2.1250	88,400	1.875
BLR-20000	1.2500	2.3750	1.500	1.125	.020	2.3750	136,500	2.093
BLR-22000	1.3750	2.5625	1.687	1.218	.020	2.5625	162,000	2.281
BLR-24000	1.5000	2.6875	1.687	1.218	.030	2.6875	170,000	2.390
BLR-26000	1.6250	2.8750	1.750	1.281	.030	2.8750	190,000	2.531
BLR-28000	*1.7500	*3.0000	1.812	1.312	.030	*3.0000	204,000	2.672
BLR-30000	*1.8750	*3.1250	1.875	1.343	.030	*3.1250	220,000	2.812
BLR-32000	*2.0000	*3.2500	1.937	1.375	.030	*3.2500	237,000	2.937
BLR-36000	*2.2500	*3.6250	2.000	1.406	.030	*3.6250	260,000	3.156
BLR-40000	*2.5000	*3.9375	2.062	1.437	.030	*3.9375	289,000	3.437
BLR-44000	*2.7500	*4.1250	2.187	1.500	.030	*4.1250	324,000	3.687
BLR-48000	*3.0000	*4.3750	2.312	1.562	.030	*4.3750	359,000	3.937

*+.0000, -.0008

NOTES:

1. ADD "G" TO PART NUMBER IF LUBRICATION GROOVE REQUIRED. EXAMPLE-BLR-8000-G.
2. ADD "C" TO PART NUMBER IF RACE TO BE CADMIUM PLATED.
3. SEE PAGES C, D, AND E FOR STAKING GROOVE AND PART NUMBER CONFIGURATIONS.



"L" SERIES